

Australian/New Zealand Standard™

**Information technology equipment—
Safety**

**Part 1: General requirements
(IEC 60950-1:2001, MOD)**



AS/NZS 60950.1:2003

This Joint Australian/New Zealand Standard was prepared by Joint Technical Committee TE-001, Safety of Electronic Equipment. It was approved on behalf of the Council of Standards Australia on 25 November 2002 and on behalf of the Council of Standards New Zealand on 24 July 2003.
This Standard was published on 15 September 2003.

The following are represented on Committee TE-001:

Australian Chamber of Commerce and Industry
Australian Communications Authority
Australian Electrical and Electronic Manufacturers Association
Australian Information Industry Association
Consumer Electronics Association of New Zealand
Consumer Electronics Suppliers Association
Department of Defence, Australia
Electrical Compliance Testing Association
Electrical Regulatory Authorities
Electricity Supply Association of Australia
Federation of Australian Commercial Television Stations
International Accreditation, New Zealand
Institution of Radio and Electronics Engineers, Australia
Ministry of Economic Development, New Zealand
Singtel Optus
Telstra

Keeping Standards up-to-date

Standards are living documents which reflect progress in science, technology and systems. To maintain their currency, all Standards are periodically reviewed, and new editions are published. Between editions, amendments may be issued. Standards may also be withdrawn. It is important that readers assure themselves they are using a current Standard, which should include any amendments which may have been published since the Standard was purchased.

Detailed information about joint Australian/New Zealand Standards can be found by visiting the Standards Web Shop at www.standards.com.au or Standards New Zealand web site at www.standards.co.nz and looking up the relevant Standard in the on-line catalogue.

Alternatively, both organizations publish an annual printed Catalogue with full details of all current Standards. For more frequent listings or notification of revisions, amendments and withdrawals, Standards Australia and Standards New Zealand offer a number of update options. For information about these services, users should contact their respective national Standards organization.

We also welcome suggestions for improvement in our Standards, and especially encourage readers to notify us immediately of any apparent inaccuracies or ambiguities. Please address your comments to the Chief Executive of either Standards Australia or Standards New Zealand at the address shown on the back cover.

This Standard was issued in draft form for comment as DR 02508.

Australian/New Zealand Standard™

Information technology equipment— Safety

Part 1: General requirements (IEC 60950-1:2001, MOD)

Originated in Australia as AS 3260—1988.
Originated in New Zealand as NZS 6600:1989.
Previous edition AS/NZS 60950:2000.
AS/NZS 60950:2000 jointly revised and redesignated as AS/NZS
60950.1:2003.
Reissued incorporating Amendment No. 1 (May 2006).
Reissued incorporating Amendment No. 2 (February 2008).
Reissued incorporating Amendment No. 3 (February 2008).

COPYRIGHT

© Standards Australia/Standards New Zealand

All rights are reserved. No part of this work may be reproduced or copied in any form or by any means, electronic or mechanical, including photocopying, without the written permission of the publisher.

Jointly published by Standards Australia, GPO Box 476, Sydney, NSW 2001 and Standards New Zealand, Private Bag 2439, Wellington 6020

PREFACE

This Standard was prepared by the Joint Standards Australia/Standards New Zealand Committee TE-001, *Safety of Electronic Equipment*, to supersede AS/NZS 60950:2000, *Safety of information technology equipment* from 1 July 2006. During this time it is anticipated that regulatory authorities will approve information technology equipment to either Standard.

This Standard incorporates Amendment No. 1 (May 2006), Amendment No. 2 (February 2008) and Amendment No. 3 (February 2008). The changes required by the Amendment are indicated in the text by a marginal bar and amendment number against the clause, note, table, figure or part thereof affected.

The objective of this Standard is to establish minimum safety requirements for the design, construction and operation of mains-powered or battery-powered information technology equipment. It sets out requirements intended to ensure the safety of the operator and other people who may come into contact with the equipment and, where specifically stated, for service personnel and which may be used as the basis for approval for Australia and New Zealand.

This Standard forms the first edition of AS/NZS 60950.1 *Information technology equipment—Safety Part 1: General requirements*.

This Standard is an adoption with national variations and contains the full text of IEC 60950-1:2001, *Information technology equipment—Safety - Part 1: General requirements*, including Corrigendum 1 (October 2002) and has been varied as indicated to take account of Australian/New Zealand conditions.

Variations to IEC 60950-1:2001 are indicated at the appropriate places throughout this standard. Strikethrough (~~example~~) identifies IEC text, tables and figures which, for the purposes of this Australian/New Zealand Standard, are deleted. Where text, tables or figures are added, each is set in its proper place and identified by shading (example). Added figures are not themselves shaded, but are identified by a shaded border.

The variations to Clauses 6.2.2, 6.2.2.1 and 6.2.2.2 apply only in Australia and are marked by A in the right hand margin. For New Zealand, the text of the IEC Standard applies and is marked by NZ in the right hand margin.

Variations made to IEC 60950-1:2001 form the Australian/New Zealand variations for the purposes of the CB scheme for recognition of testing to standards for safety of electrical equipment. These variations have been incorporated in the body of the standard. They are listed in Annex ZZ for easy reference.

In this Standard, the following print types are used:

- requirements proper: in arial type;
- *test specifications: in italic type;*
- explanatory matter: in smaller arial type.
- terms in **SMALL CAPITALS** are defined in Clause 1.2.

The terms ‘normative’ and ‘informative’ are used to define the application of the annex to which they apply. A normative annex is an integral part of a standard, whereas an informative annex is only for information and guidance.

As this Joint Standard is reproduced from an International Standard, the following applies:

- (a) The AS/NZS number is shown only on the cover and title page.

- (b) The source text ‘this International Standard’ should read ‘this Australian/New Zealand Standard’, and references to ‘relevant IEC Standard’ should read ‘relevant IEC, Australian or New Zealand Standard’.
- (c) A full point should be substituted for a comma when referring to a decimal marker.
- (d) References to International Standards in Annex P and Annex Q should be replaced by references to equivalent Australian or Australian/New Zealand Standards as listed. Australian or Australian/New Zealand Standards that are identical to the International Standard they replace, are appropriately identified. Where no relevant New Zealand or Australian/New Zealand Standard is listed, the referenced Australian Standard is deemed to be appropriate for the purpose in New Zealand.

CONTENTS

	<i>Page</i>
0 Principles of safety.....	xvi
0.1 General principles of safety	xvi
0.2 Hazards	xvii
0.2.1 Electric shock.....	xvii
0.2.2 Energy related hazards	xviii
0.2.3 Fire	xviii
0.2.4 Heat related hazards.....	xix
0.2.5 Mechanical hazards	xix
0.2.6 Radiation	xix
0.2.7 Chemical hazards	xx
0.3 Materials and components	xx
1 General.....	1
1.1 Scope	1
1.1.1 Equipment covered by this standard.....	1
1.1.2 Additional requirements	2
1.1.3 Exclusions	2
1.2 Definitions.....	3
1.2.1 Equipment electrical ratings	4
1.2.2 Operating conditions	5
1.2.3 Equipment mobility.....	5
1.2.4 Classes of equipment – Protection against electric shock.....	5
1.2.5 Connection to the supply.....	6
1.2.6 Enclosures	7
1.2.7 Accessibility	7
1.2.8 Circuits and circuit characteristics	8
1.2.9 Insulation	9
1.2.10 Clearance and creepage distances	10
1.2.11 Components.....	10
1.2.12 Flammability.....	11
1.2.13 Miscellaneous	12
1.3 General requirements	14
1.3.1 Application of requirements.....	14
1.3.2 Equipment design and construction.....	14
1.3.3 Supply voltage	14
1.3.4 Constructions not specifically covered.....	14
1.3.5 Equivalent materials.....	14
1.3.6 Orientation during transport and use	15
1.3.7 Choice of criteria.....	15
1.3.8 Examples mentioned in the standard.....	15
1.3.9 Conductive liquids.....	15
1.4 General conditions for tests	15
1.4.1 Application of tests.....	15
1.4.2 Type tests	15
1.4.3 Test samples	15
1.4.4 Operating parameters for tests.....	16

	<i>Page</i>
1.4.5	Supply voltage for tests..... 16
1.4.6	Supply frequency for tests..... 17
1.4.7	Electrical measuring instruments..... 17
1.4.8	Normal operating voltages 17
1.4.9	Measurement of voltage to earth 17
1.4.10	Loading configuration of the EUT 18
1.4.11	Power from a telecommunication network 18
1.4.12	Temperature measurement conditions..... 18
1.4.13	Temperature measurement methods 19
1.4.14	Simulated faults and abnormal conditions 19
1.4.15	Compliance by inspection of relevant data 19
1.5	Components 19
1.5.1	General..... 19
1.5.2	Evaluation and testing of components 20
1.5.3	Thermal controls 20
1.5.4	Transformers..... 20
1.5.5	Interconnecting cables 20
1.5.6	Capacitors in primary circuits 20
1.5.7	Double insulation or reinforced insulation bridged by components..... 21
1.5.8	Components in equipment for IT power distribution systems 21
1.6	Power interface..... 22
1.6.1	AC power distribution systems 22
1.6.2	Input current 22
1.6.3	Voltage limit of hand-held equipment 22
1.6.4	Neutral conductor..... 22
1.7	Markings and instructions 22
1.7.1	Power rating..... 23
1.7.2	Safety instructions 24
1.7.3	Short duty cycles..... 25
1.7.4	Supply voltage adjustment 25
1.7.5	Power outlets on the equipment 25
1.7.6	Fuse identification..... 26
1.7.7	Wiring terminals 26
1.7.8	Controls and indicators 27
1.7.9	Isolation of multiple power sources 28
1.7.10	IT power distribution systems..... 28
1.7.11	Thermostats and other regulating devices 28
1.7.12	Language..... 28
1.7.13	Durability 28
1.7.14	Removable parts..... 28
1.7.15	Replaceable batteries 28
1.7.16	Operator access with a tool..... 29
1.7.17	Equipment for restricted access locations 29
2	Protection from hazards 30
2.1	Protection from electric shock and energy hazards 30
2.1.1	Protection in operator access areas 30
2.1.2	Protection in service access areas 35
2.1.3	Protection in restricted access locations..... 36

	<i>Page</i>
2.2 SELV circuits	36
2.2.1 General requirements.....	36
2.2.2 Voltages under normal conditions	36
2.2.3 Voltages under fault conditions	36
2.2.4 Connection of SELV circuits to other circuits	37
2.3 TNV circuits	38
2.3.1 Limits.....	38
2.3.2 Separation from other circuits and from accessible parts.....	40
2.3.3 Separation from hazardous voltages	41
2.3.4 Connection of TNV circuits to other circuits.....	41
2.3.5 Test for operating voltages generated externally	42
2.4 Limited current circuits.....	42
2.4.1 General requirements.....	42
2.4.2 Limit values.....	42
2.4.3 Connection of limited current circuits to other circuits.....	43
2.5 Limited power sources	43
2.6 Provisions for earthing and bonding	45
2.6.1 Protective earthing.....	45
2.6.2 Functional earthing	45
2.6.3 Protective earthing and protective bonding conductors.....	46
2.6.4 Terminals.....	49
2.6.5 Integrity of protective earthing.....	50
2.7 Overcurrent and earth fault protection in primary circuits	51
2.7.1 Basic requirements	51
2.7.2 Faults not covered in 5.3.....	51
2.7.3 Short-circuit backup protection.....	52
2.7.4 Number and location of protective devices	52
2.7.5 Protection by several devices.....	53
2.7.6 Warning to service persons	53
2.8 Safety interlocks	54
2.8.1 General principles.....	54
2.8.2 Protection requirements	54
2.8.3 Inadvertent reactivation.....	54
2.8.4 Fail-safe operation	55
2.8.5 Moving parts	55
2.8.6 Overriding	55
2.8.7 Switches and relays	55
2.8.8 Mechanical actuators	56
2.9 Electrical insulation.....	56
2.9.1 Properties of insulating materials	56
2.9.2 Humidity conditioning	57
2.9.3 Grade of insulation.....	57
2.10 Clearances, creepage distances and distances through insulation	60
2.10.1 General.....	60
2.10.2 Determination of working voltage	61
2.10.3 Clearances.....	62
2.10.4 Creepage distances	68
2.10.5 Solid insulation	70

	<i>Page</i>
2.10.6 Coated printed boards.....	73
2.10.7 Enclosed and sealed parts.....	76
2.10.8 Spacings filled by insulating compound.....	77
2.10.9 Component external terminations.....	77
2.10.10 Insulation with varying dimensions.....	78
3 Wiring, connections and supply.....	79
3.1 General.....	79
3.1.1 Current rating and overcurrent protection.....	79
3.1.2 Protection against mechanical damage.....	79
3.1.3 Securing of internal wiring.....	79
3.1.4 Insulation of conductors.....	79
3.1.5 Beads and ceramic insulators.....	80
3.1.6 Screws for electrical contact pressure.....	80
3.1.7 Insulating materials in electrical connections.....	80
3.1.8 Self-tapping and spaced thread screws.....	81
3.1.9 Termination of conductors.....	81
3.1.10 Sleeving on wiring.....	82
3.2 Connection to an a.c. mains supply or a d.c. mains supply.....	82
3.2.1 Means of connection.....	82
3.2.2 Multiple supply connections.....	83
3.2.3 Permanently connected equipment.....	83
3.2.4 Appliance inlets.....	84
3.2.5 Power supply cords.....	84
3.2.6 Cord anchorages and strain relief.....	86
3.2.7 Protection against mechanical damage.....	87
3.2.8 Cord guards.....	87
3.2.9 Supply wiring space.....	88
3.3 Wiring terminals for connection of external conductors.....	88
3.3.1 Wiring terminals.....	88
3.3.2 Connection of non-detachable power supply cords.....	88
3.3.3 Screw terminals.....	88
3.3.4 Conductor sizes to be connected.....	89
3.3.5 Wiring terminal sizes.....	89
3.3.6 Wiring terminal design.....	90
3.3.7 Grouping of wiring terminals.....	90
3.3.8 Stranded wire.....	90
3.4 Disconnection from the mains supply.....	91
3.4.1 General requirement.....	91
3.4.2 Disconnect devices.....	91
3.4.3 Permanently connected equipment.....	91
3.4.4 Parts which remain energized.....	92
3.4.5 Switches in flexible cords.....	92
3.4.6 Single-phase and d.c. equipment.....	92
3.4.7 Three-phase equipment.....	92
3.4.8 Switches as disconnect devices.....	92
3.4.9 Plugs as disconnect devices.....	93
3.4.10 Interconnected equipment.....	93
3.4.11 Multiple power sources.....	93

		<i>Page</i>
	3.5 Interconnection of equipment.....	93
	3.5.1 General requirements.....	93
	3.5.2 Types of interconnection circuits.....	93
	3.5.3 ELV circuits as interconnection circuits.....	94
4	Physical requirements.....	95
	4.1 Stability.....	95
A2	4.1.201 Display devices used for television purposes.....	95
	4.2 Mechanical strength.....	95
	4.2.1 General.....	95
	4.2.2 Steady force test, 10 N.....	96
	4.2.3 Steady force test, 30 N.....	96
	4.2.4 Steady force test, 250 N.....	96
	4.2.5 Impact test.....	96
	4.2.6 Drop test.....	97
	4.2.7 Stress relief test.....	98
	4.2.8 Cathode ray tubes.....	98
	4.2.9 High pressure lamps.....	98
	4.2.10 Wall or ceiling mounted equipment.....	99
	4.3 Design and construction.....	99
	4.3.1 Edges and corners.....	99
	4.3.2 Handles and manual controls.....	99
	4.3.3 Adjustable controls.....	99
	4.3.4 Securing of parts.....	100
	4.3.5 Connection of plugs and sockets.....	100
	4.3.6 Direct plug-in equipment.....	100
	4.3.7 Heating elements in earthed equipment.....	100
	4.3.8 Batteries.....	101
	4.3.9 Oil and grease.....	102
	4.3.10 Dust, powders, liquids and gases.....	102
	4.3.11 Containers for liquids or gases.....	103
	4.3.12 Flammable liquids.....	103
	4.3.13 Radiation.....	103
	4.4 Protection against hazardous moving parts.....	106
	4.4.1 General.....	106
	4.4.2 Protection in operator access areas.....	107
	4.4.3 Protection in restricted access locations.....	107
	4.4.4 Protection in service access areas.....	107
	4.5 Thermal requirements.....	108
	4.5.1 Maximum temperatures.....	108
	4.5.2 Resistance to abnormal heat.....	110
	4.6 Openings in enclosures.....	110
	4.6.1 Top and side openings.....	110
	4.6.2 Bottoms of fire enclosures.....	112
	4.6.3 Doors or covers in fire enclosures.....	114
	4.6.4 Openings in transportable equipment.....	114
	4.6.5 Adhesives for constructional purposes.....	115

	<i>Page</i>
4.7	Resistance to fire..... 116
4.7.1	Reducing the risk of ignition and spread of flame 116
4.7.2	Conditions for a fire enclosure..... 116
4.7.3	Materials..... 117
4.7.201	Resistance to fire – Alternative tests..... 123
5	Electrical requirements and simulated abnormal conditions..... 127
5.1	Touch current and protective conductor current 127
5.1.1	General..... 127
5.1.2	Equipment under test (EUT)..... 127
5.1.3	Test circuit..... 127
5.1.4	Application of measuring instrument..... 129
5.1.5	Test procedure..... 129
5.1.6	Test measurements..... 130
5.1.7	Equipment with touch current exceeding 3,5 mA 131
5.1.8	Touch currents to telecommunication networks and cable distribution systems and from telecommunication networks..... 131
5.2	Electric strength..... 134
5.2.1	General..... 134
5.2.2	Test procedure..... 134
5.3	Abnormal operating and fault conditions 137
5.3.1	Protection against overload and abnormal operation 137
5.3.2	Motors..... 137
5.3.3	Transformers..... 137
5.3.4	Functional insulation 138
5.3.5	Electromechanical components 138
5.3.6	Simulation of faults 138
5.3.7	Unattended equipment 139
5.3.8	Compliance criteria for abnormal operating and fault conditions 139
6	Connection to telecommunication networks..... 141
6.1	Protection of telecommunication network service persons, and users of other equipment connected to the network, from hazards in the equipment..... 141
6.1.1	Protection from hazardous voltages 141
6.1.2	Separation of the telecommunication network from earth..... 141
6.2	Protection of equipment users from overvoltages on telecommunication networks..... 142
6.2.1	Separation requirements 142
6.2.2	Electric strength test procedure..... 143
6.3	Protection of the telecommunication wiring system from overheating 146
7	Connection to cable distribution systems..... 147
7.1	Protection of cable distribution system service persons, and users of other equipment connected to the system, from hazardous voltages in the equipment..... 147
7.2	Protection of equipment users from overvoltages on the cable distribution system..... 147
7.3	Insulation between primary circuits and cable distribution systems 148
7.3.1	General..... 148
7.3.2	Voltage surge test..... 148
7.3.3	Impulse test 148

	<i>Page</i>
Annex A Tests for resistance to heat and fire	150
A.1 Flammability test for fire enclosures of movable equipment having a total mass exceeding 18 kg and of stationary equipment (see 4.7.3.2).....	150
A.1.1 Samples.....	150
A.1.2 Conditioning of samples	150
A.1.3 Mounting of samples	150
A.1.4 Test flame	150
A.1.5 Test procedure.....	150
A.1.6 Compliance criteria	150
A.2 Flammability test for fire enclosures of movable equipment having a total mass not exceeding 18 kg, and for material and components located inside fire enclosures (see 4.7.3.2 and 4.7.3.4).....	151
A.2.1 Samples.....	151
A.2.2 Conditioning of samples	151
A.2.3 Mounting of samples	151
A.2.4 Test flame	151
A.2.5 Test procedure.....	151
A.2.6 Compliance criteria	151
A.2.7 Alternative test.....	152
A.3 Hot flaming oil test (see 4.6.2)	152
A.3.1 Mounting of samples	152
A.3.2 Test procedure.....	152
A.3.3 Compliance criterion	152
Annex B Motor tests under abnormal conditions (see 4.7.2.2 and 5.3.2).....	153
B.1 General requirements	153
B.2 Test conditions	153
B.3 Maximum temperatures.....	153
B.4 Running overload test.....	155
B.5 Locked-rotor overload test	155
B.6 Running overload test for d.c. motors in secondary circuits.....	156
B.7 Locked-rotor overload test for d.c. motors in secondary circuits	156
B.7.1 Test procedure.....	156
B.7.2 Alternative test procedure	156
B.7.3 Electric strength test	157
B.8 Test for motors with capacitors	157
B.9 Test for three-phase motors.....	157
B.10 Test for series motors	157
Annex C Transformers (see 1.5.4 and 5.3.3)	158
C.1 Overload test	158
C.2 Insulation.....	159
Annex D Measuring instruments for touch-current tests (see 5.1.4)	161
D.1 Measuring instrument.....	161
D.2 Alternative measuring instrument.....	162
Annex E Temperature rise of a winding (see 1.4.13).....	163
Annex F Measurement of clearances and creepage distances (see 2.10)	164

	<i>Page</i>
Annex G Alternative method for determining minimum clearances	171
G.1 Summary of the procedure for determining minimum clearances	171
G.2 Determination of mains transient voltage	171
G.2.1 AC mains supply	171
G.2.2 DC mains supply	172
G.3 Determination of telecommunication network transient voltage	172
G.4 Determination of required withstand voltage	173
G.5 Measurement of transient voltage levels	174
G.6 Determination of minimum clearances	174
Annex H Ionizing radiation (see 4.3.13)	177
Annex J Table of electrochemical potentials (see 2.6.5.6)	179
Annex K Thermal controls (see 1.5.3 and 5.3.7)	180
K.1 Making and breaking capacity	180
K.2 Thermostat reliability	180
K.3 Thermostat endurance test	180
K.4 Temperature limiter endurance	180
K.5 Thermal cut-out reliability	180
K.6 Stability of operation	181
Annex L Normal load conditions for some types of electrical business equipment (see 1.2.2.1 and 4.5.1)	182
L.1 Typewriters	182
L.2 Adding machines and cash registers	182
L.3 Erasers	182
L.4 Pencil sharpeners	182
L.5 Duplicators and copy machines	182
L.6 Motor-operated files	182
L.7 Other business equipment	183
Annex M Criteria for telephone ringing signals (see 2.3.1)	184
M.1 Introduction	184
M.2 Method A	184
M.3 Method B	187
M.3.1 Ringing signal	187
M.3.2 Tripping device and monitoring voltage	187
Annex N Impulse test generators (see 2.10.3.4, 6.2.2.1, 7.3.2 and clause G.5)	189
N.1 ITU-T impulse test generators	189
N.2 IEC 60065 impulse test generator	189
Annex P Normative References	192
Annex Q Bibliography	196
Annex R Examples of requirements for quality control programmes	197
R.1 Minimum separation distances for unpopulated coated printed boards (see 2.10.6)	197
R.2 Reduced clearances (see 2.10.3)	198
Annex S Procedure for impulse testing (see 6.2.2.3)	200
S.1 Test equipment	200
S.2 Test procedure	200
S.3 Examples of waveforms during impulse testing	200

	<i>Page</i>
Annex T Guidance on protection against ingress of water (see 1.1.2).....	202
Annex U Insulated winding wires for use without interleaved insulation (see 2.10.5.4).....	204
U.1 Wire construction	204
U.2 Type tests	204
U.2.1 Electric strength	204
U.2.2 Flexibility and adherence	204
U.2.3 Heat shock.....	205
U.2.4 Retention of electric strength after bending	205
U.3 Tests during manufacture	205
U.3.1 Routine testing.....	206
U.3.2 Sampling tests	206
Annex V AC power distribution systems (see 1.6.1).....	207
V.1 Introduction.....	207
V.2 TN power distribution systems	208
V.3 TT power distribution systems.....	211
V.4 IT power distribution systems.....	212
Annex W Summation of touch currents	214
W.1 Touch current from electronic circuits	214
W.1.1 Floating circuits.....	214
W.1.2 Earthed circuits	214
W.2 Interconnection of several equipments	215
W.2.1 Isolation	216
W.2.2 Common return, isolated from earth	216
W.2.3 Common return, connected to protective earth	216
Annex X Maximum heating effect in transformer tests (see clause C.1)	217
X.1 Determination of maximum input current	217
X.2 Overload test procedure.....	218
Annex Y Ultraviolet light conditioning test (see 4.3.13.3)	219
Y.1 Test apparatus.....	219
Y.2 Mounting of test samples	219
Y.3 Carbon-arc light-exposure apparatus	219
Y.4 Xenon-arc light-exposure apparatus.....	219
INDEX.....	220
Annex ZZ Variations to IEC 60950-1:2001 for application in Australia and New Zealand	262
FIGURES	
Figure 2A – Test finger.....	32
Figure 2B – Test pin	33
Figure 2C – Test probe.....	33
Figure 2D – Maximum voltages permitted after a single fault	39
Figure 2E – Test generator.....	42
Figure 2F – Examples of application of insulation	60
Figure 2G – Thermal ageing time	75
Figure 2H – Abrasion resistance test for coating layers	76
Figure 4A – Impact test using a steel ball	97

	<i>Page</i>
Figure 4B – Examples of cross-sections of designs of openings preventing vertical access	111
Figure 4C – Examples of louvre design	111
Figure 4D – Enclosure openings.....	112
Figure 4E – Typical bottom of a fire enclosure for partially enclosed component or assembly.....	113
Figure 4F – Baffle plate construction	114
Figure 5A – Test circuit for touch current of single-phase equipment on a star TN or TT power supply system.....	128
Figure 5B – Test circuit for touch current of three-phase equipment on a star TN or TT power supply system.....	129
Figure 6A – Test for separation between a telecommunication network and earth	142
Figure 6B – Application points of test voltage	144
Figure B.1 – Determination of arithmetic average temperature	154
Figure C.1 – Determination of arithmetic average temperature	159
Figure D.1 – Measuring instrument.....	161
Figure D.2 – Alternative measuring instrument	162
Figure F.1 – Narrow groove.....	164
Figure F.2 – Wide groove	165
Figure F.3 – V-shaped groove	165
Figure F.4 – Rib	165
Figure F.5 – Uncemented joint with narrow groove	166
Figure F.6 – Uncemented joint with wide groove.....	166
Figure F.7 – Uncemented joint with narrow and wide grooves.....	166
Figure F.8 – Narrow recess	167
Figure F.9 – Wide recess	167
Figure F.10 – Coating around terminals.....	168
Figure F.11 – Coating over printed wiring	168
Figure F.12 – Example of measurements in an enclosure of insulating material.....	169
Figure F.13 – Intervening, unconnected conductive part.....	170
Figure M.1 – Definition of ringing period and cadence cycle	185
Figure M.2 – I_{TS1} limit curve for cadenced ringing signal.....	186
Figure M.3 – Peak and peak-to-peak currents	186
Figure M.4 – Ringing voltage trip criteria	188
Figure N.1 – ITU-T impulse test generator circuit	189
Figure N.2 – IEC 60065 impulse test generator circuit.....	190
Figure S.1 – Waveform on insulation without surge suppressors and no breakdown	200
Figure S.2 – Waveforms on insulation during breakdown without surge suppressors	201
Figure S.3 – Waveforms on insulation with surge suppressors in operation	201
Figure S.4 – Waveform on short-circuited surge suppressor and insulation	201
Figure V.1 – Examples of TN-S power distribution systems	209
Figure V.2 – Example of TN-C-S power distribution system	210
Figure V.3 – Example of TN-C power distribution system	210

	<i>Page</i>
Figure V.4 – Example of single-phase, 3-wire TN-C power distribution system	211
Figure V.5 – Example of three line and neutral TT power distribution system	211
Figure V.6 – Example of three line TT power distribution system	212
Figure V.7 – Example of three line (and neutral) IT power distribution system	212
Figure V.8 – Example of three line IT power distribution system	213
Figure W.1 – Touch current from a floating circuit	214
Figure W.2 – Touch current from an earthed circuit	215
Figure W.3 – Summation of touch currents in a PABX	215

TABLES

1A – Voltage ranges of SELV and TNV circuits.....	9
2A – Distance through insulation of internal wiring	34
2B – Limits for inherently limited power sources	44
2C – Limits for power sources not inherently limited (overcurrent protective device required)	44
2D – Minimum size of protective bonding conductors	47
2E – Informative examples of protective devices in single-phase equipment or subassemblies	53
2F – Informative examples of protective devices in three-phase equipment.....	53
2G – Examples of application of insulation	58
2H – Minimum clearances for insulation in primary circuits and between primary and secondary circuits	64
2J – Additional clearances for insulation in primary circuits with peak working voltages exceeding the peak value of the nominal a.c. mains supply voltage.....	65
2K – Minimum clearances in secondary circuits.....	67
2L – Minimum creepage distances.....	70
2M – Insulation in printed boards.....	72
2N – Minimum separation distances for coated printed boards	74
3A – Sizes of cables and conduits for equipment having a rated current not exceeding 16 A	83
3B – Sizes of conductors.....	85
3C – Physical tests on power supply cords.....	87
3D – Range of conductor sizes to be accepted by terminals	89
3E – Sizes of terminals for mains supply conductors and protective earthing conductors	89
4A – Minimum property retention limits after UV exposure.....	104
4B – Temperature limits Part 1	109
4B – Temperature limits Part 2	109
4C – Size and spacing of openings in metal bottoms of fire enclosures	114
4D – Summary of material flammability requirements	123
5A – Maximum current.....	131
5B – Test voltages for electric strength tests - Part 1.....	135
5B – Test voltages for electric strength tests - Part 2.....	136

	<i>Page</i>
B.1 – Permitted temperature limits for motor windings (except for running overload test)	154
B.2 – Permitted temperature limits for running overload tests	154
C.1 – Permitted temperature limits for transformer windings	158
F.1 – Value of X	164
G.1 – Mains transient voltages	172
G.2 – Minimum clearances up to 2 000 m above sea level.....	175
J.1 – Electrochemical potentials (V).....	179
N.1 – Component values for figures N.1 and N.2	190
R.1 – Rules for sampling and inspection – coated printed boards	198
R.2 – Rules for sampling and inspection – reduced clearances	199
T.1 – Extract from IEC 60529:1989.....	203
U.1 – Mandrel diameter	204
U.2 – Oven temperature	205
X.1 – Test steps	217

INTRODUCTION

0 Principles of safety

The following principles have been adopted by technical committee 74 in the development of this standard.

These principles do not cover performance or functional characteristics of equipment.

Words printed in **SMALL CAPITALS** are terms that are defined in 1.2 of this standard.

0.1 General principles of safety

It is essential that designers understand the underlying principles of safety requirements in order that they can engineer safe equipment.

These principles are not an alternative to the detailed requirements of this standard, but are intended to provide designers with an appreciation of the basis of these requirements. Where the equipment involves technologies and materials or methods of construction not specifically covered, the design of the equipment should provide a level of safety not less than those described in these principles of safety.

Designers shall take into account not only normal operating conditions of the equipment but also likely fault conditions, consequential faults, foreseeable misuse and external influences such as temperature, altitude, pollution, moisture, overvoltages on the mains and overvoltages on a **TELECOMMUNICATION NETWORK** or a **CABLE DISTRIBUTION SYSTEM**.

The following priorities should be observed in determining what design measures to adopt:

- where possible, specify design criteria that will eliminate, reduce or guard against hazards;
- where the above is not practicable because the functioning of the equipment would be impaired, specify the use of protective means independent of the equipment, such as personal protective equipment (which is not specified in this standard);
- where neither of the above measures is practicable, or in addition to those measures, specify the provision of markings and instructions regarding the residual risks.

There are two types of persons whose safety needs to be considered, **USERS** (or **OPERATORS**) and **SERVICE PERSONS**.

USER is the term applied to all persons other than **SERVICE PERSONS**. Requirements for protection should assume that **USERS** are not trained to identify hazards, but will not intentionally create a hazardous situation. Consequently, the requirements will provide protection for cleaners and casual visitors as well as the assigned **USERS**. In general, **USERS** should not have access to hazardous parts, and to this end, such parts should only be in **SERVICE ACCESS AREAS** or in equipment located in **RESTRICTED ACCESS LOCATIONS**.

When **USERS** are admitted to **RESTRICTED ACCESS LOCATIONS** they shall be suitably instructed.

SERVICE PERSONS are expected to use their training and skill to avoid possible injury to themselves and others due to obvious hazards which exist in **SERVICE ACCESS AREAS** of the equipment or on equipment located in **RESTRICTED ACCESS LOCATIONS**. However, **SERVICE PERSONS** should be protected against unexpected hazards. This can be done by, for example, locating parts that need to be accessible for servicing away from electrical and mechanical hazards, providing shields to avoid accidental contact with hazardous parts, and providing labels or instructions to warn personnel about any residual risk.

Information about potential hazards can be marked on the equipment or provided with the equipment, depending on the likelihood and severity of injury, or made available for **SERVICE PERSONS**. In general, **USERS** shall not be exposed to hazards likely to cause injury, and information provided for **USERS** should primarily aim at avoiding misuse and situations likely to create hazards, such as connection to the wrong power source and replacement of fuses by incorrect types.

MOVABLE EQUIPMENT is considered to present a slightly increased risk of shock, due to possible extra strain on the supply cord leading to rupture of the earthing conductor. With **HAND-HELD EQUIPMENT**, this risk is increased; wear on the cord is more likely, and further hazards could arise if the units were dropped. **TRANSPORTABLE EQUIPMENT** introduces a further factor because it can be used and carried in any orientation; if a small metallic object enters an opening in the **ENCLOSURE** it can move around inside the equipment, possibly creating a hazard.

0.2 Hazards

Application of a safety standard is intended to reduce the risk of injury or damage due to the following:

- electric shock;
- energy related hazards;
- fire;
- heat related hazards;
- mechanical hazards;
- radiation;
- chemical hazards.

0.2.1 Electric shock

Electric shock is due to current passing through the human body. The resulting physiological effects depend on the value and duration of the current and the path it takes through the body. The value of the current depends on the applied voltage, the impedance of the source and the impedance of the body. The body impedance depends in turn on the area of contact, moisture in the area of contact and the applied voltage and frequency. Currents of approximately half a milliampere can cause a reaction in persons in good health and may cause injury indirectly due to involuntary reaction. Higher currents can have more direct effects, such as burn, muscle tetanization or ventricular fibrillation.

Steady state voltages up to 42,4 V peak, or 60 V d.c., are not generally regarded as hazardous under dry conditions for an area of contact equivalent to a human hand. Bare parts which have to be touched or handled should be at earth potential or properly insulated.

Some equipment will be connected to telephone and other external networks. Some **TELECOMMUNICATION NETWORKS** operate with signals such as voice and ringing superimposed on a steady **DC VOLTAGE**; the total may exceed the values given above for steady-state voltages. It is common practice for the **SERVICE PERSONS** of telephone companies to handle parts of such circuits bare-handed. This has not caused serious injury, because of the use of cadenced ringing and because there are limited areas of contact with bare conductors normally handled by **SERVICE PERSONS**. However, the area of contact of a part accessible to the **USER**, and the likelihood of the part being touched, should be further limited (for example, by the shape and location of the part).

It is normal to provide two levels of protection for **USERS** to prevent electric shock. Therefore, the operation of equipment under normal conditions and after a single fault, including any consequential faults, should not create a shock hazard. However, provision of additional protective measures, such as protective earthing or **SUPPLEMENTARY INSULATION**, is not considered a substitute for, or a relief from, properly designed **BASIC INSULATION**.

Harm may result from:

Contact with bare parts normally at **HAZARDOUS VOLTAGES**.

Breakdown of insulation between parts normally at **HAZARDOUS VOLTAGES** and accessible conductive parts.

Contact with circuits connected to **TELE-COMMUNICATION NETWORKS** which exceed 42,4 V peak or 60 V d.c.

Breakdown of **USER**-accessible insulation.

TOUCH CURRENT (leakage current) flowing from parts at **HAZARDOUS VOLTAGES** to accessible parts, or failure of a protective earthing connection. **TOUCH CURRENT** may include current due to EMC filter components connected between **PRIMARY CIRCUITS** and accessible parts.

0.2.2 Energy related hazards

Injury or fire may result from a short circuit between adjacent poles of high current supplies or high capacitance circuits, causing:

- burns;
- arcing;
- ejection of molten metal.

Even circuits whose voltages are safe to touch may be hazardous in this respect.

Examples of measures to reduce risks include:

- separation;
- shielding;
- provision of **SAFETY INTERLOCKS**.

0.2.3 Fire

Risk of fire may result from excessive temperatures either under normal operating conditions or due to overload, component failure, insulation breakdown or loose connections. Fires originating within the equipment should not spread beyond the immediate vicinity of the source of the fire, nor cause damage to the surroundings of the equipment.

Examples of measures to reduce risks:

Prevent **USER** access to parts at **HAZARDOUS VOLTAGES** by fixed or locked covers, **SAFETY INTERLOCKS**, etc. Discharge accessible capacitors that are at **HAZARDOUS VOLTAGES**.

Provide **BASIC INSULATION** and connect the accessible conductive parts and circuits to earth so that exposure to the voltage which can develop is limited because overcurrent protection will disconnect the parts having low impedance faults within a specified time; or provide a metal screen connected to protective earth between the parts, or provide **DOUBLE INSULATION** or **REINFORCED INSULATION** between the parts, so that breakdown to the accessible part is not likely to occur.

Limit the accessibility and area of contact of such circuits, and separate them from unearthed parts to which access is not limited.

Insulation which is accessible to the **USER** should have adequate mechanical and electrical strength to reduce the likelihood of contact with **HAZARDOUS VOLTAGES**.

Limit **TOUCH CURRENT** to a specified value, or provide a high integrity protective earthing connection.

Examples of measures to reduce risks include:

- providing overcurrent protection;
- using constructional materials having appropriate flammability properties for their purpose;
- selection of parts, components and consumable materials to avoid high temperature which might cause ignition;
- limiting the quantity of combustible materials used;
- shielding or separating combustible materials from likely ignition sources;
- using **ENCLOSURES** or barriers to limit the spread of fire within the equipment;
- using suitable materials for **ENCLOSURES** so as to reduce the likelihood of fire spreading from the equipment.

0.2.4 Heat related hazards

Injury may result from high temperatures under normal operating conditions, causing:

- burns due to contact with hot accessible parts;
- degradation of insulation and of safety-critical components;
- ignition of flammable liquids.

Examples of measures to reduce risks include:

- taking steps to avoid high temperature of accessible parts;
- avoiding temperatures above the ignition point of liquids;
- provision of markings to warn **USERS** where access to hot parts is unavoidable.

0.2.5 Mechanical hazards

Injury may result from:

- sharp edges and corners;
- moving parts which have the potential to cause injury;
- equipment instability;
- flying particles from imploding cathode ray tubes and exploding high pressure lamps.

Examples of measures to reduce risks include:

- rounding of sharp edges and corners;
- guarding;
- provision of **SAFETY INTERLOCKS**;
- providing sufficient stability to free-standing equipment;
- selecting cathode ray tubes and high pressure lamps that are resistant to implosion and explosion respectively;
- provision of markings to warn **USERS** where access is unavoidable.

0.2.6 Radiation

Injury to **USERS** and to **SERVICE PERSONS** may result from some forms of radiation emitted by equipment. Examples are sonic (acoustic), radio frequency, infra-red, ultraviolet and ionizing radiation, and high intensity visible and coherent light (lasers).

Examples of measures to reduce risks include:

- limiting the energy level of potential radiation sources;
- screening radiation sources;
- provision of **SAFETY INTERLOCKS**;
- provision of markings to warn **USERS** where exposure to the radiation hazard is unavoidable.

0.2.7 Chemical hazards

Injury may result from contact with some chemicals or from inhalation of their vapours and fumes.

Examples of measures to reduce risks include:

- avoiding the use of constructional and consumable materials likely to cause injury by contact or inhalation during intended and normal conditions of use;
- avoiding conditions likely to cause leakage or vaporization;
- provision of markings to warn **USERS** about the hazards.

0.3 Materials and components

Materials and components used in the construction of equipment should be so selected and arranged that they can be expected to perform in a reliable manner for the anticipated life of the equipment without creating a hazard, and would not contribute significantly to the development of a serious fire hazard. Components should be selected so that they remain within their manufacturers' ratings under normal operating conditions, and do not create a hazard under fault conditions.

STANDARDS AUSTRALIA/STANDARDS NEW ZEALAND

Australian/New Zealand Standard**Information technology equipment—Safety
Part 1: General requirements
(IEC 60950-1:2001, MOD)**

Any IEC table, figure or passage of text that is struck-through is not part of this Standard. Any Australian/New Zealand table, figure or passage of text that is added (and identified by shading) is part of this Standard.

1 General**1.1 Scope****1.1.1 Equipment covered by this standard**

This standard is applicable to mains-powered or battery-powered information technology equipment, including electrical business equipment and associated equipment, with a **RATED VOLTAGE** not exceeding 600 V.

This standard is also applicable to such information technology equipment:

- designed for use as telecommunication terminal equipment and **TELECOMMUNICATION NETWORK** infrastructure equipment, regardless of the source of power;
- designed and intended to be connected directly to, or used as infrastructure equipment in, a **CABLE DISTRIBUTION SYSTEM**, regardless of the source of power;
- designed to use the **AC MAINS SUPPLY** as a communication transmission medium (see NOTE 4 of clause 6 and NOTE 3 of clause 7).

This standard specifies requirements intended to reduce risks of fire, electric shock or injury for the **OPERATOR** and layman who may come into contact with the equipment and, where specifically stated, for a **SERVICE PERSON**.

This standard is intended to reduce such risks with respect to installed equipment, whether it consists of a system of interconnected units or independent units, subject to installing, operating and maintaining the equipment in the manner prescribed by the manufacturer.