

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE



---

**Low-voltage switch mode power supplies –  
Part 7: Safety requirements**

**Alimentations à découpage basse tension –  
Partie 7: Exigences de sécurité**



## THIS PUBLICATION IS COPYRIGHT PROTECTED

Copyright © 2016 IEC, Geneva, Switzerland

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

Droits de reproduction réservés. Sauf indication contraire, aucune partie de cette publication ne peut être reproduite ni utilisée sous quelque forme que ce soit et par aucun procédé, électronique ou mécanique, y compris la photocopie et les microfilms, sans l'accord écrit de l'IEC ou du Comité national de l'IEC du pays du demandeur. Si vous avez des questions sur le copyright de l'IEC ou si vous désirez obtenir des droits supplémentaires sur cette publication, utilisez les coordonnées ci-après ou contactez le Comité national de l'IEC de votre pays de résidence.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland

Tel.: +41 22 919 02 11  
Fax: +41 22 919 03 00  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)

### About the IEC

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

### About IEC publications

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigenda or an amendment might have been published.

#### IEC Catalogue - [webstore.iec.ch/catalogue](http://webstore.iec.ch/catalogue)

The stand-alone application for consulting the entire bibliographical information on IEC International Standards, Technical Specifications, Technical Reports and other documents. Available for PC, Mac OS, Android Tablets and iPad.

#### IEC publications search - [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and also once a month by email.

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

The world's leading online dictionary of electronic and electrical terms containing 20 000 terms and definitions in English and French, with equivalent terms in 15 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

#### IEC Glossary - [std.iec.ch/glossary](http://std.iec.ch/glossary)

65 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.

#### IEC Customer Service Centre - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: [csc@iec.ch](mailto:csc@iec.ch).

---

### A propos de l'IEC

La Commission Electrotechnique Internationale (IEC) est la première organisation mondiale qui élabore et publie des Normes internationales pour tout ce qui a trait à l'électricité, à l'électronique et aux technologies apparentées.

### A propos des publications IEC

Le contenu technique des publications IEC est constamment revu. Veuillez vous assurer que vous possédez l'édition la plus récente, un corrigendum ou amendement peut avoir été publié.

#### Catalogue IEC - [webstore.iec.ch/catalogue](http://webstore.iec.ch/catalogue)

Application autonome pour consulter tous les renseignements bibliographiques sur les Normes internationales, Spécifications techniques, Rapports techniques et autres documents de l'IEC. Disponible pour PC, Mac OS, tablettes Android et iPad.

#### Recherche de publications IEC - [www.iec.ch/searchpub](http://www.iec.ch/searchpub)

La recherche avancée permet de trouver des publications IEC en utilisant différents critères (numéro de référence, texte, comité d'études,...). Elle donne aussi des informations sur les projets et les publications remplacées ou retirées.

#### IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)

Restez informé sur les nouvelles publications IEC. Just Published détaille les nouvelles publications parues. Disponible en ligne et aussi une fois par mois par email.

#### Electropedia - [www.electropedia.org](http://www.electropedia.org)

Le premier dictionnaire en ligne de termes électroniques et électriques. Il contient 20 000 termes et définitions en anglais et en français, ainsi que les termes équivalents dans 15 langues additionnelles. Egalement appelé Vocabulaire Electrotechnique International (IEV) en ligne.

#### Glossaire IEC - [std.iec.ch/glossary](http://std.iec.ch/glossary)

65 000 entrées terminologiques électrotechniques, en anglais et en français, extraites des articles Termes et Définitions des publications IEC parues depuis 2002. Plus certaines entrées antérieures extraites des publications des CE 37, 77, 86 et CISPR de l'IEC.

#### Service Clients - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)

Si vous désirez nous donner des commentaires sur cette publication ou si vous avez des questions contactez-nous: [csc@iec.ch](mailto:csc@iec.ch).

# INTERNATIONAL STANDARD

# NORME INTERNATIONALE



---

**Low-voltage switch mode power supplies –  
Part 7: Safety requirements**

**Alimentations à découpage basse tension –  
Partie 7: Exigences de sécurité**

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

COMMISSION  
ELECTROTECHNIQUE  
INTERNATIONALE

---

ICS 29.200

ISBN 978-2-8322-3670-3

**Warning! Make sure that you obtained this publication from an authorized distributor.  
Attention! Veuillez vous assurer que vous avez obtenu cette publication via un distributeur agréé.**

## CONTENTS

FOREWORD.....	7
INTRODUCTION.....	10
0 Principles of safety .....	11
0.1 General.....	11
0.2 Hazards .....	12
0.2.1 General .....	12
0.2.2 Electric shock .....	12
0.2.3 Energy related hazards.....	13
0.2.4 Fire.....	13
0.2.5 Heat related hazards .....	14
0.2.6 Mechanical hazards.....	14
0.2.7 Chemical hazards .....	14
0.3 Materials and components .....	14
1 Scope.....	15
1.1 Equipment covered by this document.....	15
1.2 Exclusions .....	15
1.3 Additional requirements .....	15
2 Normative references .....	16
3 Terms and definitions .....	17
3.100 General.....	18
4 Protection against hazards .....	20
4.1 General.....	20
4.1.100 Constructions not specifically covered .....	21
4.1.101 Orientation during transport and use.....	21
4.2 Fault and abnormal conditions .....	21
4.2.100 Application of faults and abnormal conditions .....	22
4.3 Short circuit and overload protection.....	22
4.4 Protection against electric shock.....	23
4.4.1 General .....	23
4.4.2 Decisive voltage class .....	23
4.4.3 Provision for basic protection.....	25
4.4.4 Provision for fault protection .....	26
4.4.5 Enhanced protection.....	27
4.4.6 Protective measures .....	30
4.4.7 Insulation.....	31
4.4.8 Compatibility with residual current-operated protective devices (RCD).....	37
4.4.9 Capacitor discharge.....	37
4.5 Protection against electrical energy hazards .....	38
4.5.1 Operator access areas.....	38
4.5.2 Service access areas.....	38
4.6 Protection against fire and thermal hazards .....	38
4.6.1 Circuits representing a fire hazard .....	38
4.6.2 Components representing a fire hazard .....	38
4.6.3 Fire enclosures.....	38
4.6.4 Temperature limits.....	40
4.6.5 Limited power sources .....	41

4.7	Protection against mechanical hazards .....	41
4.7.1	General .....	41
4.7.2	Specific requirements for liquid cooled SMPS .....	41
4.8	Equipment with multiple sources of supply .....	41
4.9	Protection against environmental stresses .....	41
4.10	Protection against sonic pressure hazards .....	41
4.11	Wiring and connections .....	41
4.11.1	General .....	41
4.11.2	Routing.....	41
4.11.3	Colour coding .....	41
4.11.4	Splices and connections .....	41
4.11.5	Accessible connections .....	41
4.11.6	Interconnections between parts of the SMPS .....	42
4.11.7	Supply connections.....	42
4.11.8	Terminals .....	42
4.12	Enclosures.....	42
4.12.1	General .....	42
4.12.2	Handles and manual controls.....	42
4.12.3	Cast metal .....	43
4.12.4	Sheet metal .....	43
4.12.5	Stability test for enclosure .....	43
5	Test requirements.....	43
5.1	General.....	43
5.1.1	Test objectives and classification.....	43
5.1.2	Selection of test samples .....	43
5.1.3	Sequence of tests .....	43
5.1.4	Earthing conditions .....	43
5.1.5	General conditions for tests .....	43
5.1.6	Compliance .....	44
5.1.7	Test overview .....	44
5.2	Test specifications .....	46
5.2.1	Visual inspections (type test, sample test and routine test) .....	46
5.2.2	Mechanical tests.....	46
5.2.3	Electrical tests .....	48
5.2.4	Abnormal operation and simulated faults tests .....	56
5.2.5	Material tests.....	61
5.2.6	Environmental tests (type tests).....	61
5.2.7	Hydrostatic pressure test (type test and routine test) .....	62
6	Information and marking requirements .....	62
6.1	General.....	62
6.2	Information for selection .....	64
6.2.100	Additional marking requirements for SMPS .....	64
6.2.101	Additional information for Component SMPS .....	66
6.3	Information for installation and commissioning .....	66
6.3.1	General .....	66
6.3.2	Mechanical considerations.....	66
6.3.3	Environment .....	66
6.3.4	Handling and mounting .....	66
6.3.5	Enclosure temperature.....	66

6.3.6	Connections .....	66
6.3.7	Protection requirements.....	67
6.3.8	Commissioning.....	69
6.4	Information for use.....	69
6.4.1	General .....	69
6.4.2	Adjustment .....	69
6.4.3	Labels, signs and signals.....	69
6.5	Information for maintenance.....	69
6.5.1	General .....	69
6.5.2	Capacitor discharge.....	69
6.5.3	Auto restart/bypass connection.....	69
6.5.4	Other hazards.....	69
6.5.5	Equipment with multiple sources of supply.....	69
6.5.100	Disconnect device external to permanently connected equipment.....	70
6.5.101	Power cord acting as disconnecting device.....	70
7	Components .....	70
7.1	General.....	70
7.2	Switches .....	71
7.2.1	General .....	71
7.2.2	Requirements for switches acting as disconnecting device .....	71
7.2.3	Requirements for switches.....	72
7.2.4	Test method and compliance criteria .....	73
7.3	Overtemperature protection devices (thermal cut-offs or thermal links) .....	73
7.4	PTC thermistors.....	74
7.5	Overcurrent protective devices.....	74
7.6	Protective devices not mentioned in 7.2 to 7.5 .....	74
7.6.1	Other protective devices requirements.....	74
7.6.2	Compliance and test method.....	74
7.7	Transformers .....	74
7.7.1	General .....	74
7.7.2	Insulation.....	75
7.8	Motors .....	76
7.9	Mains supply cords .....	76
7.9.1	General .....	76
7.9.2	Fitting of non-detachable mains supply cords .....	77
7.10	Surge Protective Devices (SPDs).....	79
7.10.1	Use of an SPD connected to reliable earthing .....	79
7.10.2	Use of an SPD between mains and protective earth.....	79
7.10.3	Bridging of supplementary, double or reinforced insulation by a SPD.....	79
7.10.4	Circuits or components used as transient voltage limiting devices .....	79
7.11	Wound components .....	80
7.12	IC current limiters .....	80
7.12.1	General .....	80
7.12.2	Test program 1 .....	81
7.12.3	Test program 2 .....	81
7.12.4	Test program 3 .....	81
7.13	Capacitors and RC units bridging insulation .....	82
7.14	Optocouplers bridging insulation .....	84
7.15	Relays .....	84

7.16 Electrolytic capacitors .....	85
Annex A (normative) Additional information for protection against electric shock .....	86
Annex B (informative) Considerations for the reduction of the pollution degree .....	88
Annex C (informative) Symbols referred to in IEC 62477-1 .....	89
Annex D (normative) Evaluation of clearance and creepage distances .....	90
Annex E (informative) Altitude correction for clearances .....	91
Annex F (normative) Clearance and creepage distance determination for frequencies greater than 30 kHz .....	92
Annex G (informative) Cross-sections of round conductors .....	93
Annex H (informative) Guidelines for RCD compatibility .....	94
Annex I (informative) Examples of overvoltage category reduction .....	95
Annex J (informative) Burn thresholds for touchable surfaces .....	96
Annex K (informative) Table of electrochemical potentials .....	97
Annex L (informative) Measuring instrument for touch current measurements .....	98
Annex M (informative) Test probes for determining access .....	99
Annex AA (normative) <i>Addition</i> Insulated winding wires for use without interleaved insulation .....	100
Annex AB (informative) Minimum and maximum cross-section of copper conductors suitable for connection to terminals for external conductors .....	103
Annex AC (normative) DC power and distribution equipment .....	104
Annex AD (informative) <i>Addition</i> Examples of protective measures according to IEC 61204-7 clause 4.4.1 – 4.4.5 for protection against electrical shock .....	119
Bibliography .....	121
Figure 100 – Electric strength test instrument .....	53
Figure 101 – Mandrel .....	54
Figure 102 – Initial position of mandrel .....	55
Figure 103 – Final position of mandrel .....	55
Figure 104 – Position of metal foil on insulating material .....	55
Figure 105 – Determination of arithmetic average temperature .....	60
Figure 106 – Detachable mains supply cords and connections .....	77
Figure AC.100 – Resistance and short circuit calculations .....	107
Table 5 – Voltage limits .....	24
Table 6 – Separation requirements for circuit under consideration .....	25
Table 100 – Limits for access of current .....	29
Table 101 – Tests for insulation in non-separable layers .....	36
Table 22 – Test overview .....	45
Table 102 – Temperature limits for transformer windings .....	60
Table 36 – Information requirements .....	63
Table 103 – Component requirements .....	71
Table 104 – Peak surge current .....	73
Table 105 – Strain relief test force .....	78
Table 106 – Capacitor ratings according to IEC 60384-14 .....	83

Table C.100 – Symbols .....	89
Table AA.1 – Mandrel diameter .....	101
Table AA.2 – Oven temperature .....	101
Table AB.1 – Cross-section of copper conductors suitable for connection to terminals for external conductors (extract from IEC 61439-1) .....	103
Table AC.101 – AC and DC field wiring spacings .....	111
Table AC.102 – Minimum acceptable spacings for uninsulated bus bars .....	112
Table AC.103 – Temperature limits .....	113
Table AC.104 – Switch test sequences .....	115

# INTERNATIONAL ELECTROTECHNICAL COMMISSION

---

## LOW-VOLTAGE SWITCH MODE POWER SUPPLIES –

### Part 7: Safety requirements

#### FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 61204-7 has been prepared by subcommittee 22E: Stabilized power supplies, of IEC technical committee 22: Power electronic systems and equipment.

This second edition cancels and replaces the first edition published in 2006. This edition constitutes a complete technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) use of IEC 62477-1 as reference document, instead of IEC 60950-1;
- b) modification of the title by deleting the wording “DC output-“ and adding “switch mode”.

IEC 61204-7 has the status of a product standard.

The text of this document is based on the following documents:

FDIS	Report on voting
22E/175/FDIS	22E/177/RVD

Full information on the voting for the approval of this document can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 61204 series, published under the general title *Low-voltage power supplies, d.c. output*, can be found on the IEC website.

Future standards in this series will carry the new general title as cited above. Titles of existing standards in this series will be updated at the time of the next edition.

This International Standard is to be read in conjunction with IEC 62477-1:2012.

NOTE A consolidated version is under consideration.

The provisions of the general rules dealt with in IEC 62477-1:2012 are only applicable to this document insofar as they are specifically cited. Clauses and subclauses of IEC 62477-1:2012 that are applicable in this document are identified by reference to the reference document, for example, 4.3 of IEC 62477-1:2012.

Subclauses that are numbered starting from 100 are additional to those in IEC 62477-1:2012.

Additional tables and figures in this document are numbered starting from 100.

New annexes in this document are lettered AA, AB, AC, etc.

Wherever the word **PECS (power electronic converter system)** occurs in this reference document, this means **SMPS**.

The wordings **SMPS** and "power supply" are considered to be identical throughout this document.

References of the reference document to clauses or tables, which have been modified in this document, shall be read as reference to the relevant clauses or tables of this document.

Refer to 3.100 for further information on how to read this document.

In this document, the following print types are used:

- Requirements proper and normative annexes: in roman type.
- Notes and other informative matter: in smaller roman type.
- Normative conditions within tables: in smaller roman type.
- Terms that are defined in clause 3 or IEC 62477-1:2012: **Bold Italic**.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

**IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.**

## INTRODUCTION

IEC 62477-1:2012, used by this document as a reference, relates to products that include power electronic converters, with a rated system voltage not exceeding 1 000 V AC or 1 500 V DC. It specifies requirements to reduce risks of fire, electric shock, thermal, energy and mechanical hazards, except functional safety as defined in IEC 61508 (all parts). The objectives of this standard are to establish a common terminology and basis for the safety requirements of products that contain power electronic converters across several IEC technical committees.

IEC 62477-1:2012 was developed with the intention

- to be used as a reference document for product committees inside IEC technical committee 22: Power electronic systems and equipment in the development of product standards for power electronic converter systems and equipment,
- to replace IEC 62103 as a product family standard providing minimum requirements for safety aspects of power electronic converter systems and equipment in apparatus for which no product standard exists, and

NOTE The scope of IEC 62103 contains reliability aspects, which are not covered by this document.

- to be used as a reference document for product committees outside TC 22 in the development of product standards of power electronic converter systems and equipment intended for renewable energy sources. TC 82, TC 88, TC 105 and TC 114, in particular, have been identified as relevant technical committees at the time of publication.

As such, IEC technical sub-committee 22E: Stabilized switched-mode power supplies carefully considered the relevance of each paragraph of IEC 62477-1:2012 for the SMPS and referenced, added, replaced or modified requirements as relevant. This is because product-specific topics not covered by the reference document are the responsibility of the technical committee using the reference document.

The reference document, being a group safety standard, will not take precedence over this product-specific standard according to IEC Guide 104. IEC Guide 104 provides information about the responsibility of product committees to use group safety standards for the development of their own product standards.

## LOW-VOLTAGE SWITCH MODE POWER SUPPLIES –

### Part 7: Safety requirements

#### 0 Principles of safety

Safety principles of this document follow the concepts of IEC Guide 116 and Annex D of CENELEC Guide 32:2014.

NOTE The principles of safety are mainly adopted from IEC 60950-1:2005/AMD1:2009/AMD2:2013.

##### 0.1 General

The following principles have been adopted by IEC technical committee 22E in the development of this document. These principles do not cover performance or functional characteristics of equipment.

It is essential that designers understand the underlying principles of safety requirements in order that they can engineer safe equipment.

These principles are not an alternative to the detailed requirements of this document, but are intended to provide designers with an appreciation of the basis of these requirements. Where the equipment involves technologies, components and materials or methods of construction not specifically covered, the design of the equipment should provide a level of safety not less than that described in these principles of safety.

NOTE The need for additional detailed requirements to cope with a new situation is brought promptly to the attention of the appropriate committee.

Designers will take into account not only normal operating conditions of the equipment but also likely fault conditions, consequential faults, foreseeable misuse and external influences such as temperature, altitude, pollution, moisture, overvoltages on the **mains supply** and **non-mains supply**.

Dimensioning of insulation spacings should take account of possible reductions by manufacturing tolerances, or where deformation could occur due to handling, shock and vibration likely to be encountered during manufacture, transport and normal operation.

The following priorities should be observed in determining what design measures to adopt:

- where possible, specify design criteria that will eliminate, reduce or guard against hazards;
- where the above is not practicable because the functioning of the equipment would be impaired, specify the use of protective means independent of the equipment, such as personal protective equipment (which is not specified in this document);
- where neither of the above measures is practicable, or in addition to those measures, specify the provision of markings and instructions regarding the residual risks.

There are two types of persons whose safety needs to be considered, **operators** (or **users**) and **service persons**.

**Operator** is the term applied to all persons other than **service persons**. Requirements for protection should assume that **operators** are not trained to identify hazards, but will not intentionally create a hazardous situation. Consequently, the requirements will provide protection for cleaners and casual visitors as well as the assigned **operators**. In general,

**operators** should not have access to hazardous parts, and to this end, such parts should only be in service access area or in equipment located in **restricted access areas**.

When **operators** are admitted to **restricted access areas (RAA)** they shall be suitably instructed.

NOTE The term "restricted access area" (RAA) is also known as "restricted access location" (RAL).

**Service persons** are expected to use their training and skill to avoid possible injury to themselves and others due to obvious hazards that exist in service access areas of the equipment or on equipment located in **restricted access areas**. However, **service persons** should be protected against unexpected hazards. This can be done by, for example, locating parts that need to be accessible for servicing away from electrical and mechanical hazards, providing shields to avoid accidental contact with hazardous parts, and providing labels or instructions to warn personnel about any residual risk.

Information about potential hazards can be marked on the equipment or provided with the equipment, depending on the likelihood and severity of injury, or made available for **service persons**. In general, **operators** shall not be exposed to hazards likely to cause injury, and information provided for **operators** should primarily aim at avoiding misuse and situations likely to create hazards, such as connection to the wrong power source and replacement of fuses by incorrect types.

**Moveable equipment** is considered to present a slightly increased risk of shock, due to possible extra strain on the supply cord leading to rupture of the earthing conductor. With hand-held equipment, this risk is increased; wear on the cord is more likely, and further hazards could arise if the units were dropped. **Transportable equipment** introduces a further factor because it can be used and carried in any orientation; if a small metallic object enters an opening in the **enclosure**, it can move around inside the equipment, possibly creating a hazard.

## 0.2 Hazards

### 0.2.1 General

Application of a safety standard is intended to reduce the risk of injury or damage due to the following:

- electric shock;
- energy related hazards;
- fire;
- heat related hazards;
- mechanical hazards;
- chemical hazards.

NOTE Radiation hazard are not included, as LEDs used for the purpose of indication and display only are not considered to cause hazardous radiation (e.g. like high intense lighting LEDs).

### 0.2.2 Electric shock

Electric shock is due to current passing through the human body. The resulting physiological effects depend on the value and duration of the current and the path it takes through the body. The value of the current depends on the applied voltage, the impedance of the source and the impedance of the body. The body impedance depends in turn on the area of contact, moisture in the area of contact and the applied voltage and frequency.

Currents of approximately half a milliamp can cause a reaction in persons in good health and may cause injury indirectly due to involuntary reaction. Higher currents can have more direct

effects such as burn or muscle tetanisation leading to inability to let go or to ventricular fibrillation.

It is normal to provide two levels of protection for **operators** to prevent electric shock. Therefore, the operation of equipment under normal conditions and after a single fault, including any consequential faults, should not create a shock hazard.

Harm may result from

- 1) contact with hazardous-live-parts,
- 2) breakdown of insulation between **hazardous-live-parts** and accessible conductive parts,
- 3) contact with circuits above **DVC As** limits,
- 4) breakdown of **operator** accessible insulation, and
- 5) **touch current** (leakage current) flowing from **hazardous-live-parts** to accessible parts, or failure of a **protective earthing** connection. **Touch current** may include current due to EMC filter components.

### 0.2.3 Energy related hazards

Injury or fire may result from a short-circuit between adjacent poles of high current supplies or high capacitance circuits, causing

- burns,
- arcing, and
- ejection of molten metal.

Even circuits whose voltages are safe to touch may be hazardous in this respect.

Examples of measures to reduce risks include:

- separation;
- shielding;
- provision of safety interlocks.

NOTE Safety interlocks are not described within this document.

### 0.2.4 Fire

Risk of fire may result from excessive temperatures either under normal operating conditions or due to overload, component failure, insulation breakdown or loose connections. Fires originating within the equipment should not spread beyond the immediate vicinity of the source of the fire, nor cause damage to the surroundings of the equipment.

Examples of measures to reduce risks include:

- providing overcurrent protection;
- using constructional materials having appropriate flammability properties for their purpose;
- selection of parts, components and consumable materials to avoid high temperature which might cause ignition;
- limiting the quantity of combustible materials used;
- shielding or separating combustible materials from likely ignition sources;
- using **enclosures** or barriers to limit the spread of fire within the equipment;
- using suitable materials for **enclosures** so as to reduce the likelihood of fire spreading from the equipment.

### 0.2.5 Heat related hazards

Injury may result from high temperatures under normal operating conditions, causing

- burns due to contact with hot accessible parts,
- degradation of insulation and of safety-critical components, and
- ignition of flammable liquids.

Examples of measures to reduce risks include:

- taking steps to avoid high temperature of accessible parts;
- avoiding temperatures above the ignition point of liquids;
- provision of markings to warn **operators** where access to hot parts is unavoidable.

### 0.2.6 Mechanical hazards

Injury may result from

- sharp edges and corners,
- moving parts that have the potential to cause injury,
- equipment instability,
- sonic pressure, and
- flying particles from exploding components (like electrolytic capacitors).

Examples of measures to reduce risks include:

- rounding of sharp edges and corners;
- guarding;
- providing sufficient stability to free-standing equipment;
- selecting suitable components, for example electrolytic capacitors with integral pressure relief to avoid explosion;
- provision of markings to warn **operators** where access is unavoidable.

### 0.2.7 Chemical hazards

Injury may result from contact with some chemicals or from inhalation of their vapours and fumes.

Examples of measures to reduce risks include:

- avoiding the use of constructional and consumable materials likely to cause injury by contact or inhalation during intended and normal conditions of use;
- avoiding conditions likely to cause leakage or vaporization;
- provision of markings to warn **operators** about the hazards.

## 0.3 Materials and components

Materials and components used in the construction of equipment should be so selected and arranged that they can be expected to perform in a reliable manner for the anticipated life of the equipment without creating a hazard, and would not contribute significantly to the development of a serious fire hazard. Components should be selected so that they remain within their manufacturers' ratings under normal operating conditions, and do not create a hazard under fault conditions.

## 1 Scope

### 1.1 Equipment covered by this document

This part of IEC 61204 specifies the safety requirements for **switch mode power supply (SMPS)** units supplied by source voltages up to 1 000 V AC or 1 500 V DC providing AC and/or DC output(s), except inverter output(s) establishing AC mains (see exceptions in 1.2).

NOTE 1 This document by definition covers DC-DC converters.

NOTE 2 Power supplies may provide accessory AC mains socket outlets, when such outputs are supplied from the AC mains.

This product standard covers both **stand-alone** and **component SMPS** as defined in this document. **DC power and distribution equipment** which provides, distributes, monitors, and controls isolated **secondary circuit** power to other equipment typically used in information and communication technology equipment installations (refer to Annex AC).

Equipment which is within the scope of Annex AC consists of some or all of the following:

- distribution panelboards, powerboards, disconnects, and overcurrent protective devices;
- control and monitoring equipment;
- assemblies consisting of: racks, shelves, and enclosures which could contain any of the above components, interconnecting hardware, **power supplies** (such as rectifiers, converters, and inverters), batteries, and any other related peripheral devices.

Where no standards exist, use of this document for other applications is not precluded.

### 1.2 Exclusions

This document does not cover:

- functional safety aspects as covered by for example IEC 61508 (all parts);
- reliability and risk considerations (e.g. related to power loss);
- information and communication technology equipment other than **SMPS** to such apparatus;
- electrical equipment and systems for railways applications and electric vehicles.
- motor-generator sets;
- uninterruptible power supplies (UPS);
- direct plug-in power units;
- power supplies according to IEC 61558 (all parts) covering linear power supply units incorporating safety isolating transformers providing **SELV** or **PELV** output(s) in accordance with IEC 60364-4-41 and **SMPS** for use with household and other consumer products;
- transformers covered by IEC 61558-1;
- step-down converters covered by IEC 60146-1-1;
- **SMPS** and converters for use with or in products covered by IEC 61347-2-2;
- **AC or DC mains supply** distribution equipment which is part of the building wiring system and not an integral part of the equipment used in **DC power and distribution equipment**, batteries, the design or installation of **DC power and distribution** conductors and other building installation wiring (not covered by Annex AC).

### 1.3 Additional requirements

Requirements additional to those specified in this document may be necessary for