

Superseded by AS 2326.1-1991

Under revision see DR 90128

AS 2326, Part 1—1980
UDC 621.314.214.332

RECONFIRMED
1987

*October
TAS.*

Australian Standard 2326, Part 1—1980

ON-LOAD TAP-CHANGERS

Part 1—REQUIREMENTS

[Title allocated by Defence Cataloguing Authority:

TAP CHANGING SET, TRANSFORMER (On-load, General
Requirements) . . . NSC 6110]



STANDARDS ASSOCIATION OF AUSTRALIA

Incorporated by Royal Charter



THE FOLLOWING SCIENTIFIC, INDUSTRIAL AND GOVERNMENTAL ORGANIZATIONS and departments were officially represented on the committee entrusted with the preparation of this standard:

Australian-British Trade Association
Australian Electrical and Electronic Manufacturers Association
Confederation of Australian Industry
Defence Standardization Committee
Electrical Testing Laboratories
Electricity Supply Association of Australia
Electricity Supply Engineers Association of N.S.W.
Railways of Australia Committee
The Institution of Engineers, Australia

This standard, prepared by Committee EL/8, Static Electrical Machinery, was approved on behalf of the Council of the Standards Association of Australia on 22 October 1979, and was published on 1 February 1980.

To keep abreast of progress in industry, Australian standards are subject to continuous review and are kept up-to-date by the issue of amendments or revised editions as necessary. It is important therefore that standards users ensure that their standards are up-to-date. Full details of all SAA publications will be found in the Annual List of Australian Standards; these details are supplemented by monthly listings in the SAA journal 'The Australian Standard'. Information on the Annual List and 'The Australian Standard' may be obtained from any sales office of the Association, where details are also available of the current status of individual standards. Suggestions for improvements to published standards, addressed to the head office of the Association, are welcomed.

AUSTRALIAN STANDARD

ON-LOAD TAP-CHANGERS

Part 1

REQUIREMENTS

AS 2326, Part 1-1980

First published (as AS C378)	1967
Revised and issued as AS 2326, Part 1	1980

22 JAN 1980

**PUBLISHED BY THE STANDARDS ASSOCIATION OF AUSTRALIA
STANDARDS HOUSE, 80 ARTHUR ST, NORTH SYDNEY, N.S.W.**

ISBN 0 7262 1823 5

PREFACE

This standard was prepared by the Association's Committee on Static Electrical Machinery as the revision of AS C378 — 1967, which it accordingly supersedes.

The standard is Part 1 of a two-part standard. It sets out requirements for on-load tap-changers for power transformers and their motor driven mechanisms; Part 2 is an application guide to assist in the selection of suitable on-load tap-changers.

This standard is based closely on IEC 214, On-load Tap-changers, and only minor changes have been introduced. Where the standard diverges from IEC 214, this is indicated by a rule in the margin.

It is intended that this standard should be used with reference to revisions of AS C61 — 1970, Power Transformers, and AS 1078, Part 1 — 1972, Guide to Loading of Oil-immersed Transformers; and to AS 1931, Part 1 — 1976, High Voltage Testing Techniques.

Attention is drawn to the following:

- ~~AS C61 — 1970 is similar to superseded editions of IEC 76~~
- AS 1078, Part 1 — 1972 is a loading guide to AS C61 — 1963
- AS 1931, Part 1 — 1976 is based on IEC 60.

This standard may require reference to the following Australian standards:

AS 1265 Bushings for Alternating Voltages Above 1000 V

AS 1939 Classification of Degrees of Protection Provided by Enclosures for Electrical Equipment.

© Copyright — STANDARDS ASSOCIATION OF AUSTRALIA 1980

Users of standards are reminded that copyright subsists in all SAA publications. No part of this publication may be reproduced, stored in a retrieval system in any form or transmitted by any means without prior permission in writing of the Standards Association of Australia.

CONTENTS

	<i>Page</i>
SECTION 1. SCOPE AND GENERAL	
1.1 Scope	4
1.2 Service Conditions	4
1.3 Information Required With Tenders and Orders	4
SECTION 2. DEFINITIONS	
2.1 Definitions Relating to On-load Tap-changers (excluding motor-drive mechanisms)	5
2.2 Definitions Relating to Motor-drive Mechanisms	6
SECTION 3. REQUIREMENTS FOR ON-LOAD TAP-CHANGERS	
3.1 Rated Characteristics	7
3.2 Design and Construction	7
3.3 Type Tests	7
3.4 Routine Tests	11
3.5 Nameplate	11
SECTION 4. REQUIREMENTS FOR MOTOR-DRIVE MECHANISMS FOR ON-LOAD TAP-CHANGERS	
4.1 Design and Construction	12
4.2 Type Tests	12
4.3 Routine Tests	12
4.4 Nameplate	13
APPENDICES	
A — Supplementary Information on Switching Duty Relating to Tap-changers with Resistor Transition Only	14
B — Method of Determining the Equivalent Temperature of the Transition Resistor Using Power Pulse Currents	18
C — Simulated Circuits for Service Duty and Breaking Capacity Tests ..	19

STANDARDS ASSOCIATION OF AUSTRALIA

Australian Standard
for
ON-LOAD TAP CHANGERS

PART 1 — REQUIREMENTS

SECTION 1. — SCOPE AND GENERAL

1.1 SCOPE. This standard applies to on-load tap-changers* for power transformers, and their motor-drive mechanisms. It relates mainly to insulating-liquid immersed tap-changers, but air-insulated tap-changers are not excluded and the conditions should be suitably modified.

NOTE: For the purposes of this standard, oil and synthetic insulating liquids are referred to as insulating liquids. This does not imply that a synthetic insulating liquid can be used in any liquid-immersed tap-changer regardless of whether it is designed for it.

Tap-changers for transformers for railway rolling stock are excluded from this standard.

In selecting a tap-changer for a particular application, reference should be made to AS 2326, On-load Tap-changers, Part 2 — Application Guide.

1.2 SERVICE CONDITIONS.

- (a) *Temperature of tap-changer environment.* Unless more onerous conditions are specified by the purchaser, tap-changers are regarded as suitable for operation over the ranges of temperature given in Table 1.1.

TABLE 1.1
TEMPERATURE OF TAP-CHANGER
ENVIRONMENT

Tap-changer environment	Temperature	
	min.	max.
Air	-25°C	40°C
Insulating liquid	-25°C	100°C

NOTES TO TABLE 1.1:

- The tap-changer environment is the medium immediately surrounding the complete tap-changer i.e., if the latter is enclosed in a separate external container, intended for mounting outside the transformer tank, the tap-changer environment is 'Air'; if the complete tap-changer is intended for mounting inside the main transformer tank and not in a separate external container, then the tap-changer environment is 'Insulating liquid' (i.e. the liquid in the transformer tank).
 - The value of 100°C quoted above is based on a maximum ambient temperature of 40°C as specified in AS, Power Transformers.†
- (b) *Temperature of motor-drive mechanism environment.* Unless more onerous conditions are specified by the purchaser, motor-drive mechanisms are regarded as being suitable for operation in any ambient temperature between -25°C and 40°C.
- (c) *Overload conditions.* Tap-changers may be required to operate under conditions of transformer overload as specified by the transformer purchaser. Reference should be made to AS 2326, Part 2, Clauses 2.3.2 and 5.4 for further information.

NOTE: Tap-changers, like other switching devices, usually have a shorter thermal time constant than electromagnetic devices of the same current ratings.

1.3 INFORMATION REQUIRED WITH TENDERS AND ORDERS. For the information required with tenders and orders, see AS 2326, Part 2, Clause 5.

* See Note to Clause 2.1.1.

† Revised edition of AS C61 in course of preparation.