

Australian/New Zealand Standard™

Safety of machinery

Part 1603: Design of controls, interlocks and guards — Prevention of unexpected start-up



AS/NZS 4024.1603:2019

This Joint Australian/New Zealand Standard™ was prepared by Joint Technical Committee SF-041, Safety of Machinery. It was approved on behalf of the Council of Standards Australia on 29 April 2019 and by the New Zealand Standards Approval Board on 3 July 2019.

This Standard was published on 29 July 2019.

The following are represented on Committee SF-041:

- Austmine
- Australian Industry Group
- Australian Manufacturing Technology Institute
- Australian Manufacturing Workers Union
- Australian Packaging and Processing Machinery Association
- Human Factors and Ergonomics Society of Australia
- Engineers Australia
- New Zealand Safety Council
- NSCA Foundation
- NSW Department of Planning and Environment
- Safety Institute of Australia
- SafeWork NSW
- SafeWork SA
- Swinburne University of Technology
- University of Melbourne
- Winery Engineering Association (Australia)
- Workplace Health and Safety Queensland
- WorkSafe New Zealand
- WorkSafe Victoria

This Standard was issued in draft form for comment as DR AS/NZS 4024.1603:2019.

Keeping Standards up-to-date

Ensure you have the latest versions of our publications and keep up-to-date about Amendments, Rulings, Withdrawals, and new projects by visiting:

www.standards.org.au

www.standards.govt.nz

ISBN 978 1 76072 530 3

Australian/New Zealand Standard™

Safety of machinery

Part 1603: Design of controls, interlocks and guards — Prevention of unexpected start-up

Originated as part of AS 4024.1(Int)—1992.
Previous edition part of AS 4024.1—1996.
Revised in part and redesignated as AS 4024.1603—2006.
Jointly revised and redesignated as AS/NZS 4024.1603:2019.

COPYRIGHT

© ISO 2019 — All rights reserved

© Standards Australia Limited/the Crown in right of New Zealand, administered by the New Zealand Standards Executive 2019

All rights are reserved. No part of this work may be reproduced or copied in any form or by any means, electronic or mechanical, including photocopying, without the written permission of the publisher, unless otherwise permitted under the Copyright Act 1968 (Cth) or the Copyright Act 1994 (New Zealand).

Preface

This Standard was prepared by the Joint Standards Australia/Standards New Zealand Committee SF-041, Safety of Machinery, to supersede AS 4024.1603—2006, *Safety of machinery, Part 1603: Design of controls, interlocks and guards — Prevention of unexpected start-up* and its Amendment No. 1 (2015).

The objective of this Standard is to specify requirements for designed-in means aimed at preventing unexpected machine start-up (see Clause 3.2) to allow safe human interventions in danger zones (see Annex A).

This Standard applies to unexpected start-up from all types of energy source, i.e.:

- (a) power supply, e.g. electrical, hydraulic, pneumatic;
- (b) stored energy due to, e.g. gravity, compressed springs; and
- (c) external influences, e.g. from wind.

This Standard does not specify performance levels or safety integrity levels for safety-related parts of control systems. While available means to prevent unexpected start-up are identified, this document does not specify the means for the prevention of unexpected machine start-up for specific machines.

NOTE An AS 4024.3400 series Standard or an ISO/EN type-C Standard (where there is no equivalent Australian or Australian/New Zealand Standard) can define the required means for the prevention of harm arising from unexpected start-up. Otherwise, the requirements for a specific machine need to be determined by risk assessment outside the scope of this document, refer to AS/NZS 4024.1201 and AS/NZS 4024.1303 for further information on risk assessment.

This Standard is identical with, and has been reproduced from, ISO 14118:2017, *Safety of machinery — Prevention of unexpected start-up*.

As this document has been reproduced from an International Standard, a full point substitutes for a comma when referring to a decimal marker.

Australian or Australian/New Zealand Standards that are identical adoptions of international normative references may be used interchangeably. Refer to the online catalogue for information on specific Standards.

The terms “normative” and “informative” are used in Standards to define the application of the appendices or annexes to which they apply. A “normative” appendix or annex is an integral part of a Standard, whereas an “informative” appendix or annex is only for information and guidance.

Contents

Preface	ii
Foreword	iv
Introduction	v
1 Scope	1
2 Normative references	1
3 Terms and definitions	1
4 General measures to prevent unexpected start-up	2
4.1 General	2
4.2 Manual measures for isolation and energy dissipation	3
4.3 Other means to prevent unexpected (unintended) start-up	3
4.4 Signalling and warning (delayed start)	3
5 Isolation and energy dissipation	3
5.1 Prevention of unexpected start-up upon restoration of any power supplies	3
5.2 Devices for isolation from power supplies	3
5.3 Locking (securing) devices	4
5.4 Devices for stored-energy dissipation or restraint (containment)	4
5.4.1 General	4
5.4.2 Mechanical elements	5
5.4.3 Locking or securing facilities for the restraint (containment) devices	5
6 Other measures to prevent unexpected start-up	5
6.1 Design strategy	5
6.2 Measures to prevent unintended generation of start commands	6
6.2.1 Measures to prevent unintended actuation of manual start controls	6
6.2.2 Design of safety-related parts of the control system	7
6.2.3 Selection and location of power control elements	7
6.3 Measures to maintain stop commands	7
6.3.1 Principle	7
6.3.2 Maintained stop command generated by a stop control device (level A)	7
6.3.3 Maintained stop command generated by machine control (level B/C)	8
6.3.4 Mechanical disconnection (level D; see Figure 1)	8
6.3.5 Moving-part immobilization (level E; see Figure 1)	8
6.4 Automatic monitoring of the safe state (stopped condition) during a category 2 stop	8
7 Design requirements for verification	8
7.1 General	8
7.2 Provisions for verifying isolation	9
7.3 Provisions for verifying energy dissipation or restraint (containment)	9
Annex A (informative) Examples of tasks which can require the presence of persons in danger zones	10
Bibliography	11

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular the different approval criteria needed for the different types of ISO documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation on the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT) see the following URL: www.iso.org/iso/foreword.html.

This document was prepared by Technical Committee ISO/TC 199, *Safety of machinery*.

This second edition cancels and replaces the first edition (ISO 14118:2000), which has been technically revised and contains the following changes:

- the text has been edited to facilitate implementation of this document;
- the Scope has been redefined to exclude the specification of performance levels or safety integrity levels for safety-related parts of control systems;
- [Figure 1](#) has been updated.

Introduction

The structure of safety standards in the field of machinery is as follows:

- a) type-A standards (basic safety standards) giving basic concepts, principles for design, and general aspects that can be applied to all machinery;
- b) type-B standards (generic safety standards) dealing with one safety aspect or one or more type(s) of safeguard that can be used across a wide range of machinery:
 - type-B1 standards on particular safety aspects (e.g. safety distances, surface temperature, noise);
 - type-B2 standards on safeguards (e.g. two-hand controls, interlocking devices, pressure sensitive devices, guards);
- c) type-C standards (machine safety standards) dealing with detailed safety requirements for a particular machine or group of machines.

This document is a type-B standard as stated in ISO 12100.

This document is of relevance, in particular, for the following stakeholder groups representing the market players with regard to machinery safety:

- machine manufacturers (small, medium and large enterprises);
- health and safety bodies (regulators, accident prevention organizations, market surveillance, etc.)

Others can be affected by the level of machinery safety achieved with the means of the document by the above-mentioned stakeholder groups:

- machine users/employers (small, medium and large enterprises);
- machine users/employees (e.g. trade unions, organizations for people with special needs);
- service providers, e.g. for maintenance (small, medium and large enterprises);
- consumers (in case of machinery intended for use by consumers).

The above-mentioned stakeholder groups have been given the possibility to participate at the drafting process of this document.

In addition, this document is intended for standardization bodies elaborating type-C standards.

The requirements of this document can be supplemented or modified by a type-C standard.

For machines which are covered by the scope of a type-C standard and which have been designed and built according to the requirements of that standard, the requirements of that type-C standard take precedence.

Keeping a machine in a stopped condition while persons are present in danger zones is one of the most important conditions of the safe use of machinery and hence, one of the major aims of the machine designer and machine user.

In the past, the concepts of “operating machine” and “stopped machine” were generally unambiguous; a machine was

- operating when its movable elements or some of them were moving;
- stopped when its movable elements were at rest.

Machine automation has made the relationship between “operating” and “moving” on one hand and “stopped” and “at rest” on the other hand, more difficult to define. Automation has also increased the

potential for unexpected start-up and a significant number of hazardous events have occurred where machines, stopped for diagnostic work or corrective actions, started up unexpectedly.

Hazards other than mechanical hazards generated by movable elements (e.g. from a laser beam) also need to be taken into account.

The risk assessment relating to the presence of persons in a danger zone of a stopped machine needs to take into account the probability of an unexpected start-up of the hazard-generating elements.

This document provides machine designers and machinery safety standard technical committees with samples of built-in measures which can be used to prevent unexpected start-up.

Australian/New Zealand Standard

Safety of machinery

Part 1603: Design of controls, interlocks and guards — Prevention of unexpected start-up

1 Scope

This document specifies requirements for designed-in means aimed at preventing unexpected machine start-up (see 3.2) to allow safe human interventions in danger zones (see Annex A).

This document applies to unexpected start-up from all types of energy source, i.e.:

- power supply, e.g. electrical, hydraulic, pneumatic;
- stored energy due to, e.g. gravity, compressed springs;
- external influences, e.g. from wind.

This document does not specify performance levels or safety integrity levels for safety-related parts of control systems. While available means to prevent unexpected start-up are identified, this document does not specify the means for the prevention of unexpected machine start-up for specific machines.

NOTE A type-C standard can define the required means for the prevention of harm arising from unexpected start-up. Otherwise, the requirements for a specific machine need to be determined by risk assessment outside the scope of this document.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ISO 12100:2010, *Safety of machinery — General principles for design — Risk assessment and risk reduction*

ISO 13849-1, *Safety of machinery — Safety-related parts of control systems — Part 1: General principles for design*

IEC 62061, *Safety of machinery — Functional safety of safety-related electrical, electronic and programmable electronic control systems*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in ISO 12100 and the following apply.

ISO and IEC maintain terminological databases for use in standardization at the following addresses:

- ISO Online browsing platform: available at <http://www.iso.org/obp>
- IEC Electropedia: available at <http://www.electropedia.org/>

3.1

start-up

machine start-up

change from rest to motion or switch-on of a machine or of one of its parts

Note 1 to entry: An example of function other than motion is switch-on of a laser.