

ANSI/ESD SP10.1-2016

ESD Association Standard Practice

ANSI/ESD SP10.1-2016
Revision of ANSI/ESD SP10.1-2007

*For the Protection of Electrostatic
Discharge Susceptible Items-*

Automated Handling Equipment (AHE)

*Electrostatic Discharge Association
7900 Turin Road, Bldg 3
Rome, NY 13440-2069*



*An American National Standard
Approved May 3, 2016*

*ESD Association Standard Practice
for the Protection of Electrostatic Discharge
Susceptible Items –
Automated Handling Equipment (AHE)*

Approved February 25, 2016
ESD Association, Inc.



**CAUTION
NOTICE**

Electrostatic Discharge Association (ESDA) standards and publications are designed to serve the public interest by eliminating misunderstandings between manufacturers and purchasers, facilitating the interchangeability and improvement of products and assisting the purchaser in selecting and obtaining the proper product for his particular needs. The existence of such standards and publications shall not in any respect preclude any member or non-member of the Association from manufacturing or selling products not conforming to such standards and publications. Nor shall the fact that a standard or publication is published by the Association preclude its voluntary use by non-members of the Association whether the document is to be used either domestically or internationally. Recommended standards and publications are adopted by the ESDA in accordance with the ANSI Patent policy.

Interpretation of ESDA Standards: The interpretation of standards in-so-far as it may relate to a specific product or manufacturer is a proper matter for the individual company concerned and cannot be undertaken by any person acting for the ESDA. The ESDA Standards Chairman may make comments limited to an explanation or clarification of the technical language or provisions in a standard, but not related to its application to specific products and manufacturers. No other person is authorized to comment on behalf of the ESDA on any ESDA Standard.

**DISCLAIMER OF
WARRANTIES**

THE CONTENTS OF ESDA'S STANDARDS AND PUBLICATIONS ARE PROVIDED "AS-IS," AND ESDA MAKES NO REPRESENTATIONS OR WARRANTIES, EXPRESSED OR IMPLIED, OF ANY KIND WITH RESPECT TO SUCH CONTENTS. ESDA DISCLAIMS ALL REPRESENTATIONS AND WARRANTIES, INCLUDING WITHOUT LIMITATION, WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR USE, TITLE AND NON-INFRINGEMENT.

**DISCLAIMER OF
GUARANTY**

ESDA STANDARDS AND PUBLICATIONS ARE CONSIDERED TECHNICALLY SOUND AT THE TIME THEY ARE APPROVED FOR PUBLICATION. THEY ARE NOT A SUBSTITUTE FOR A PRODUCT SELLER'S OR USER'S OWN JUDGEMENT WITH RESPECT TO ANY PARTICULAR PRODUCT DISCUSSED, AND ESDA DOES NOT UNDERTAKE TO GUARANTEE THE PERFORMANCE OF ANY INDIVIDUAL MANUFACTURERS' PRODUCTS BY VIRTUE OF SUCH STANDARDS OR PUBLICATIONS. THUS, ESDA EXPRESSLY DISCLAIMS ANY RESPONSIBILITY FOR DAMAGES ARISING FROM THE USE, APPLICATION, OR RELIANCE BY OTHERS ON THE INFORMATION CONTAINED IN THESE STANDARDS OR PUBLICATIONS.

**LIMITATION ON
ESDA's LIABILITY**

NEITHER ESDA, NOR ITS MEMBERS, OFFICERS, EMPLOYEES OR OTHER REPRESENTATIVES WILL BE LIABLE FOR DAMAGES ARISING OUT OF, OR IN CONNECTION WITH, THE USE OR MISUSE OF ESDA STANDARDS OR PUBLICATIONS, EVEN IF ADVISED OF THE POSSIBILITY THEREOF. THIS IS A COMPREHENSIVE LIMITATION OF LIABILITY THAT APPLIES TO ALL DAMAGES OF ANY KIND, INCLUDING WITHOUT LIMITATION, LOSS OF DATA, INCOME OR PROFIT, LOSS OF OR DAMAGE TO PROPERTY AND CLAIMS OF THIRD PARTIES.

Published by:

**Electrostatic Discharge Association
7900 Turin Road, Bldg. 3
Rome, NY 13440**

Copyright © 2016 by ESD Association
All rights reserved

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Printed in the United States of America
ISBN: 1-58537-287-0

(This foreword is not part of ESD Association Standard Practice ANSI/ESD SP10.1-2016)

FOREWORD

Recent years have witnessed an increasing use of automation in the electronics industry. There is hardly a device, circuit board, or assembly that does not undergo one or more types of automated handling at some point during its production cycle. Further, circuit density for most semiconductor devices has steadily increased, leading to a higher ESD susceptibility for some semiconductor devices. As a result, extensive measures are required to protect these sensitive devices during manufacture.

Many of the same methods used to deal with static charge on a workbench have been applied to automated handling equipment. Grounding, the use of static dissipative materials, and ionization are techniques commonly used to deal with static charge. Automated handling equipment (AHE) presents additional problems for effective static control. Devices may become polarized by an electric field, or charge can be induced onto a device that is grounded in the presence of the electrostatic field. Also, a charge can be generated by contact with or separation from various materials. Components of AHE, particularly when integral with thermal chambers, generally require the use of easily charged materials. Grounding of sliding or rotating components may also be a challenge. These are some common problems encountered by both manufacturers and users of automated equipment. ESD control methods should be verified periodically. Test methods are needed to insure grounding integrity and verify that product does not acquire an unacceptable level of static charge during its passage through automated equipment.

In order to achieve suitable ESD control in AHE, it may be necessary to monitor or verify electrostatic charge on a product as it passes through the equipment. This can provide both continuous verification of ESD counter-measures and a method for locating sources of charge generation.

Various types of measuring devices have been developed to determine the electrostatic potential or estimate the charge on product as it passes through the equipment. In order to verify the performance of these measuring devices, it is necessary to have a means of testing their repeatability and calibration, both at manufacture and periodically during service. This standard practice¹ has been developed to assist in the generation of meaningful, repeatable data using these measuring devices.

The diverse range of handling equipment, environments, and device sensitivities may require modifications to the test apparatus described in this standard practice. Further, the test conditions and results given within this standard practice may not always represent acceptable performance. Specifications should be agreed upon between the user and manufacturer of the automatic handling equipment in each application.

This document was originally designated ESD SP10.1-2000 and was approved on February 6, 2000. ANSI/ESD SP10.1-2007 was a reaffirmation of ESD SP10.1-2000 and was approved on June 27, 2007. ANSI/ESD SP10.1-2016 is a revision of ANSI/ESD SP10.1-2007 and was approved on February 25, 2016.

¹ **ESD Association Standard Practice (SP):** A procedure for performing one or more operations or functions that may or may not yield a test result. Note, if a test result is obtained it may not be reproducible.

At the time ANSI/ESD SP10.1-2016 was approved, the 10.0 Handlers Subcommittee had the following members:

	Thomas Albano, Interim Chair Harris Space and Intelligence Systems	
Rejean Dion Bystat International, Inc.	Vladimir Kraz OnFILTER	Jeff Salisbury Finisar Corporation
Arnold Steinman Electronics Workshop	Julius Turangan Dou Yee Enterprises	Scott Ward, TAS Rep Texas Instruments

The following individuals made significant contributions to ANSI/ESD SP10.1-2016:

Donn Bellmore Advanced ESD Services+	Donald Pritchard Monroe Electronics
---	--

At the time ANSI/ESD SP10.1-2007 was approved, the 10.0 Handlers Subcommittee had the following members:

	Donn Bellmore, Chair Universal Instruments Corp.	
Don Boehm Dou Yee Enterprises	Rejean Dion Bystat International, Inc.	Jay Hamlin Medtronic
Vladimir Kraz 3M	Donald Pritchard Monroe Electronics	Arnold Steinman MKS, Ion Systems
David Swenson Affinity Static Control Consulting, LLC		Julius Turangan Western Digital

At the time ESD SP10.1-2000 was approved, the 10.0 Handlers Subcommittee had the following members:

	Joseph Bernier, Chair Intersil	
Thomas Albano Eastman Kodak Company	Donn Bellmore Universal Instruments	Donald Boehm Novx Corporation
Ken Hansen Tellabs	John Kinnear IBM	Thomas Mohler Raytheon Systems
Charles Perry Monroe Electronics	Donald Pritchard Trek, Inc.	Arnold Steinman Ion Systems
	Craig Zander, Secretary Restronics Company, Inc.	

The following individuals made significant contributions to ESD SP10.1-2000:

Wayne Tan
Advanced Micro Devices

Rita Shartzler
Motorola

TABLE OF CONTENTS

1.0 PURPOSE, SCOPE, AND APPLICATION	1
1.1 PURPOSE	1
1.2 SCOPE	1
1.3 APPLICATION	1
2.0 REFERENCED PUBLICATIONS	2
3.0 DEFINITIONS	2
4.0 SAFETY REQUIREMENTS	2
4.1 ELECTRICAL – GENERAL	2
4.2 ELECTRICAL – AUTOMATIC HANDLING EQUIPMENT.....	2
4.3 ENVIRONMENTAL	3
5.0 MEASUREMENT EQUIPMENT	3
5.1 RESISTANCE MEASUREMENTS – APPARATUS	3
5.2 CHARGE ACCUMULATION MEASUREMENTS.....	3
6.0 TEST PROCEDURES – RESISTANCE MEASUREMENTS	4
6.1 TEST PREPARATIONS – 24 HOURS PRIOR TO MEASUREMENTS	4
6.2 TEST DATA REPORTING	4
6.2.1 <i>General Information</i>	4
6.2.2 <i>Required Measurements</i>	5
7.0 TEST PROCEDURES – CHARGE ACCUMULATION MEASUREMENT	5
7.1 TEST PREPARATIONS – DYNAMIC TEST	5
7.2 MEASUREMENT CORRELATION – DYNAMIC TEST	5
7.2.1 <i>Correlation Samples – Integrated Circuit</i>	6
7.2.2 <i>Correlation Samples – PC Board</i>	6
7.2.3 <i>Correlation Testing</i>	7
7.3 TEST PREPARATIONS – STATIC TEST	7
7.4 TEST DATA REPORTING	8
7.4.1 <i>General Information</i>	8
7.5 MEASURING DEVICES ON THE AHE.....	8

ANNEXES

Annex A (Informative): Suggested Equipment Grounding Guidelines 9
Annex B (Informative): Selection of Electrostatic Voltmeters..... 10
Annex C (Informative): Recommendations on Installation of the Voltage or Electrostatic Field
Sensor 11
Annex D (Informative): Sample Data Sheet 12
Annex E (Informative): Sample Test Report Form 13
Annex F (Informative): Bibliography 15
Annex G (Informative): Revision History of ANSI/ESD SP10.1-2016..... 16

FIGURES

Figure 1: Example of Measurement Points on an Automated Handler 11

ESD Association Standard Practice for the Protection of Electrostatic Discharge Susceptible Items – Automated Handling Equipment (AHE)

1.0 PURPOSE, SCOPE, AND APPLICATION

1.1 Purpose

This standard practice provides test procedures for evaluating the electrostatic environment associated with AHE.

This document provides testing and data reporting procedures for the evaluation of ESD ground integrity in AHE and for the evaluation of charge generation and accumulation on devices in AHE. These methods evaluate newly installed and existing equipment by verifying the equipment's existing ground paths and by determining if charge on ESD-sensitive devices (ESDS) can be detected.

1.2 Scope

This standard practice covers resistance-to-ground measurements of machine components and sources of charge in AHE.

Two methods are described to measure sources of charge.

One method measures charge indirectly by measuring the voltage or field associated with the charge.

The second method directly measures the voltage induced on ESDS items.

In particular, it establishes test procedures for:

- the measurement of DC electrical resistance between machine components of AHE and the equipment grounding conductor (EGC). See Annex A.
- testing AHE to determine whether charge is being generated on devices as they move through the equipment.
- reporting the correlation between measured voltages and known test voltages as they apply to AHE. (Charge measuring devices are not addressed in this document.)

Grounding methods and materials specified herein may or may not provide adequate grounding for conditions other than steady state DC. Reactance considerations at any frequency are beyond the scope of this document. In addition, this standard practice does not determine the effectiveness of any grounding method for reducing electromagnetic interference (EMI). Explosive, ordnance, or flammable materials handling considerations are also excluded from this standard practice.

1.3 Application

Test procedures contained within this standard practice may be used by both AHE manufacturers and users to produce repeatable data describing the ground integrity of AHE and the charge generated and accumulated on specific package types during normal operating usage of the AHE. Since there is a wide variety of device sensitivities, AHE types, package types and environmental conditions, users and manufacturers are strongly urged to agree upon appropriate specifications, measurement accuracies, modifications, or additions to the tests described herein. This standard practice relies upon point-to-point DC resistance measurements taken from machine components of concern or the equipment chassis to the EGC.